

Connecting Linksys (or Cisco) to Voice Carrier



From the Phone:

1. Press the Dog Eared Paper button for main menu.
2. Press 9 or scroll down to "Network".
3. Scroll down to either A) Current IP or B) Non-DHCP IP Address.
4. Find IP address (format such as 192.168.1.***)

From your Computer next to the SIP phone:

1. Open your Internet Explorer or Firefox browser.
2. Enter in the IP address you found above. No password needed.
3. Click on the "Admin login" (top right corner), then click "Advanced." Click on the "EXT".
4. Scroll down to the "Proxy:" field and enter your Voice Carrier PBX URL (e.g., abcfirm.callingcloud.net).
5. In "Display Name" and "User ID" enter which extension number you wish to program (e.g., 101).
6. Enter the password associated with the extension (from Device Options "Secret" field in your Admin PBX).
7. Scroll all the way down and click "Submit All Changes"

Dial *43, if you enter an echo test you may hang up, this lets you know that the phone will work with our service.

Connecting the Aastra 673i to Voice Carrier



Find the IP address from the Phone:

1. Press the button "Options"
2. Scroll down to "Phone Status" using the toggle up or down button
3. IP & MAC Addresses
4. The IP address will be listed in format similar to 192.168.1.***

From your computer, next to the Aastra SIP Phone:

1. Open your internet browser and enter the IP Address with just raw numbers "192.168.1.***"
2. A screen should be displayed asking for login and password.
 - a. Login: admin
 - b. Password: 22222
3. Click on "Global SIP" below the heading on the right side titled "Advanced Settings"
4. Enter the extension number in "Authentication Name" field
5. Enter password for the extension in the "Password" field
6. Proxy Server is your Voice Carrier PBX URL (e.g., abcfirm@callingcloud.net)
7. Proxy Port is set at 5060
8. Registrar Server is the same as the Proxy Server with Registrar Port 5060
9. Click Save Setting button at the bottom
10. Once the screen has reloaded please click on "Line 1" right below "Global SIP"
11. Screen Name past the extension number
12. Authentication Name is extension number
13. Password is the extension password
14. Repeat steps 10-12 with the same information but in the "Line 1"
15. Click "Save Setting"

Dial *43, if you enter an echo test you may hang up, this lets you know that the phone will work with our service.